

Fluke 8808A Digital Multimeter

Extended Specifications

Making measurements is as simple as pushing a button

The Fluke 8808A 5.5 digit multimeter has a broad range of functions, measuring volts, ohms and amps with a basic V dc accuracy of 0.01 %. It is remarkably easy to use, even by unskilled operators, because it makes the measurements you perform most often extremely easy and fast to do.

Six setup buttons on the 8808A front panel operate like a car radio's station presets. Simply set up the meter for a common measurement, then press shift followed by a setup button (S1 to S6) to save the setup. Now each time you perform that measurement, you simply press the appropriate setup key. It's that easy!

The setup buttons eliminate the need to follow complex work instruction sheets. Operators no longer need to press multiple buttons to set up a measurement function and range, test limits, or enter other parameters to make a measurement.

Eliminate production mistakes

The Fluke 8808A 5.5 digit multimeter dependably performs the most common measurements required by today's applications.



Features at a glance

- 5.5 digit resolution
- Basic V dc accuracy of 0.01 %
- Dual display
- Dedicated dc leakage current measurement
- 2x4 ohms 4-wire measurement technique
- Six dedicated buttons for fast access to instrument setups
- Hi.Lo limit compare for Pass/Fail testing
- Fluke 45 remote command emulation

Whether you are performing functional tests or making critical measurements on test points, using the limit compare mode with pass/fail indicators eliminates production mistakes, especially those where results are "on the edge."

The 8808A display has built-in enunciators that clearly show the operator whether a test passes or fails. The pass/fail indicators take the guesswork out of testing: the result is either within limits or it's out.

8808A Specifications

Voltage

100V Setting ...	90 V to 110 V
120V Setting ...	108 V to 132 V
220V Setting ...	198 V to 242 V
240V Setting ...	216 V to 264 V
Frequency ...	47 Hz to 440 Hz.
Power Consumption ...	15 VA peak (10 W average)

Dimensions

Height ...	88 mm (3.46 in)
Width ...	217 mm (8.56 in)
Depth ...	297 mm (11.7 in)
Weight ...	2.1 kg (4.6 lbs)

Display

Vacuum Fluorescent Display, segment

Environment

Temperature

Operating ...	0 rC to 50 rC
Storage...	-40 rC to 70 rC
Warm Up...	½ hour to full uncertainty specifications

Relative Humidity (non-condensing)

Operating ...	Uncontrolled (< 10°C)
	<90 % (10 °C to 30 °C)
	<75 % (30 °C to 40 °C)
	<45 % (40 °C to 50 °C)
Storage ...	-40 rC to 70 rC <95 %

Altitude

Operating ...	2,000 Meters
Storage ...	12,000 Meters
Vibration ...	Complies with MIL-PRF-28800F Class 3

Safety

Complies with IEC 61010-1:2001, ANSI/ISA 61010-1 (S82.02.01):2004, UL 61010-1:2004, CAN/CSA C22.2 No. 61010.1:2004, CAT I 1000V/CAT II 600 V.

EMC

Designed to comply with IEC 61326-1:1997+A1:1998+A2:2000

Triggering

Trigger Delay ...	400 ms
External Trigger Delay ...	<2 ms
External Trigger Jitter ...	<1 ms
Trigger Input ...	TTL Levels
Trigger Output5 V max

Math Functions

Min/max, relative, hold, compare and dB functions.

Electrical

Input Protection ...	1000 V all ranges
Overrange ...	10 % on the largest ranges of all functions except continuity and diode test

Remote Interfaces

RS-232C

Warranty

One year

Electrical Specifications

Accuracy specifications are valid for 5-½ digit mode and after at least a half-hour warm-up.

DC Voltage Specifications

Maximum Input1000 V on any range.
Common Mode Rejection120 dB at 50 or 60 Hz @0.1% (1 k Ω unbalance)
Normal Mode Rejection80 dB at Slow Rate
A/D Nonlinearity15 ppm of range
Input Bias Current<30 pA at 25 rC
Settling ConsiderationsMeasurement settling times are affected by source impedance, cable dielectric characteristics, and input signal changes

Input Characteristics

Range	Full-Scale (5-1/2 Digits)	Resolution			Input Impedance
		Slow	Medium	Fast	
200 mV	199.999 mV	1 μ V	10 μ V	10 μ V	>10 G ^[1]
2 V	1.99999 V	10 μ V	100 μ V	100 μ V	>10 G ^[1]
20 V	19.9999 V	100 μ V	1000 μ V	1000 μ V	10 M \pm 1 %
200 V	199.999 V	1 mV	10 mV	10 mV	10 M \pm 1 %
1000 V	1000.00 V	10 mV	100 mV	100 mV	10 M \pm 1 %

Notes:
 [1] At some dual display measurements, the input impedance of 200 mV and 2 V ranges may be changed to 10 M .

Accuracy

Range	Accuracy ^[1]		Temperature Coefficient/ $^{\circ}$ C Outside 18 - 28 $^{\circ}$ C
	90 days	1 year	
	23 $^{\circ}$ C \pm 5 $^{\circ}$ C		
200 mV	0.01 + 0.003	0.015 + 0.004	0.0015 + 0.0005
2 V	0.01 + 0.002	0.015 + 0.003	0.001 + 0.0005
20 V	0.01 + 0.003	0.015 + 0.004	0.0020 + 0.0005
200 V	0.01 + 0.002	0.015 + 0.003	0.0015 + 0.0005
1000 V	0.01 + 0.002	0.015 + 0.003	0.0015 + 0.0005

Notes:
 [1] Accuracy given as \pm (% of reading + % of range)

Resistance

Specifications are for 4-wire resistance function, or 2-wire resistance with REL. If REL is not used, add 0.2 for 2-wire resistance plus lead resistance.

Measurement MethodCurrent source referenced to LO input
 .10 % of range per lead for 200 , 2 k ranges. 1 k per lead on all other ranges.
 Max Lead Resistance (4-wire ohms)... ..1000 V on all ranges
 Input ProtectionInput Characteristics

Range	Full-Scale (5-1/2 Digits)	Resolution			Current Source
		Slow	Medium	Fast	
200	199.999	0.001	0.01	0.01	0.8 mA
2 k	1.99999 k	0.01	0.1	0.1	0.8 mA
20 k	19.9999 k	0.1	1	1	0.08 mA
200 k	199.999 k	1	10	10	0.008 mA
2 M	1.99999 M	10	100	100	0.9 μA
20 M	19.9999 M	100	1 k	1 k	0.16 μA
100 M	100.000 M	1 k	10 k	10 k	0.16 μA 10 M

Accuracy

Range	Accuracy ^[1]		Temperature Coefficient/°C Outside 18 - 28 °C
	90 days	1 year	
	23 °C ± 5 °C		
200	0.02 + 0.004	0.03 + 0.004	0.003 + 0.0006
2 k	0.015 + 0.002	0.02 + 0.003	0.003 + 0.0005
20 k	0.015 + 0.002	0.02 + 0.003	0.003 + 0.0005
200 k	0.015 + 0.002	0.02 + 0.003	0.003 + 0.0005
2 M	0.03 + 0.003	0.04 + 0.004	0.004 + 0.0005
20 M	0.2 + 0.003	0.25 + 0.003	0.01 + 0.0005
100 M	1.5 + 0.004	1.75 + 0.004	0.2 + 0.0005

Notes:
 [1] Accuracy given as ± (% of reading + % of range)

DC Current

Input ProtectionTool accessible 11 A / 1000 V and 440 mA / 1000 V fuses.
 Shunt Resistance0.01 for 2 A and 10 A ranges
 1 for 20 mA and 200 mA
 Burden voltage < 1 mV for 200 uA and 2 mA range.

Input Characteristics

Range	Full-Scale (5-1/2 Digits)	Resolution			Burden Voltage
		Slow	Medium	Fast	
200 uA	199.999 μA	0.001 μA	0.01 μA	0.01 μA	<1 mV
2 mA	1999.99 μA	0.01 μA	0.1 μA	0.1 μA	<1 mV
20 mA	19.9999 mA	0.1 μA	1 μA	1 μA	<0.05 V
200 mA	199.999 mA	1 μA	10 μA	10 μA	<0.5 V
2 A	1.99999 A	10 μA	100 μA	100 μA	<0.1 V
10 A	10.0000 A	100 μA	1 mA	1 mA	<0.5 V

Frequency

Gate Time... .131 ms
 Measurement MethodAC-coupled input using the ac voltage measurement function. ...When measuring frequency after a dc offset voltage change, errors may occur. For the most accurate measurement, wait up to 1 second to allow input blocking RC time constant to settle.
 Settling Considerations ...
 Measurement ConsiderationsTo minimize measurement errors, shield inputs from external noise when measuring low voltage, low frequency signals.

Accuracy

Range	Frequency	Accuracy		Temperature Coefficient/°C Outside 18 - 28 °C
		90 days	1 year	
		23 °C + 5 °C		
100 mV to 750 V ^[1,2]	20 Hz - 2 kHz	0.01 + 0.002	0.01 + 0.003	0.002 + 0.001
	2 kHz - 20 kHz	0.01 + 0.002	0.01 + 0.003	0.002 + 0.001
	20 kHz - 200 kHz	0.01 + 0.002	0.01 + 0.003	0.002 + 0.001
	200 kHz - 1 MHz	0.01 + 0.004	0.01 + 0.006	0.002 + 0.002
Notes: [1] Input > 100 mV [2] Limited to 8* 10 ⁷ V Hz				

Continuity

Continuity Threshold20
 Test Currents1 mA
 Response Time100 samples/sec with audible tone
 Rate..... Fast
 Maximum Reading.....199.99
 Resolution.....0.01

Diode Test

Response Time100 samples/sec with audible tone
 Rate.....Fast
 Maximum Reading.....1.9999 V
 Resolution.....0.1 mV

Ordering information

Models	Description
8808A 120V	5.5 Digit Multimeter
8808A 220V	5.5 Digit Multimeter
8808A 100V	5.5 Digit Multimeter
8808A 240V	5.5 Digit Multimeter

8808A/SU includes

8808A package plus, FlukeView Forms basic software, USB to RS-232 interface adapter cable.

8808A/SU 120V	5.5 Digit Multimeter, SW USB Cable Kit
8808A/SU 220V	5.5 Digit Multimeter, SW USB Cable Kit
8808A/SU 100V	5.5 Digit Multimeter, SW USB Cable Kit
8808A/SU 240V	5.5 Digit Multimeter, SW USB Cable Kit

8808A includes

Meter, TL71 test leads, line cord, spare line fuse, statement of cal practices, WEEE information sheet, Warranty statement, Getting Started guide (English, French, German, Spanish, Italian, Simplified Chinese, Japanese), CD Rom with user manual (English).

Fluke. *Keeping your world
up and running.*®



Power Tech International Group
sales@powertech-group.com
www.powertech-group.com