

Fluke 9040 Phase Rotation Indicator



Phase rotation indicator with high voltage capability for industrial applications

The Fluke 9040 is effective for measuring phase rotation in all areas where three phase supplies are used to feed motors, drives and electrical systems. The Fluke 9040 is a rotary field indicator and can provide clear indication of the 3 phase via an LCD display and the phase rotation direction to determine correct connections. It allows rapid determination of phase sequence and has a voltage (up to 700 V) and frequency range suitable for commercial and industrial applications. The included test probes have a variable clamping range for safe contact, also in industrial sockets.

Features

- 3 phase indication
- Indication of phase rotation
- Clear LCD display
- No battery required

Technical Specifications

▪ Technical Specifications	
Voltage range	40-700 V
Frequency range	15-400 Hz
Operating timer	Continuous
Environmental Specifications	
Operating temperature	0 Â°C to 40 Â°C

Dust/water resistance	IP 40
Safety Specifications	
Electrical Safety	EN 61010, EN 61557-7
Overvoltage category	CAT III, 600 V
Mechanical & General Specifications	
Size	124 x 61 x 27 mm
Weight	200 g
Power supply	From unit under test
Warranty	2 years



Power Tech International Group
sales@powertech-group.com
www.powertech-group.com